

Power capacity

The required power supply capacity and heat emission will vary depending on the robot type and number of axes.

Using the following table as a general guide consider the required power supply preparation and control panel size, controller installation, and cooling method.

(1) When connected to SCARA robot

Robot type				Power capacity (VA)	Generated heat amount (W)
Standard type	Clean type	Dust-proof & drip-proof type	Wall-mount / Ceiling-mount / inverse type		
YK180X, 220X	–	–	–	500	63
YK250XG, 350XG, 400XG 500XGL, 600XGL	YK250XGC, 350XGC, 400XGC 500XGLC, 600XGLC	YK250XGP, 350XGP, 400XGP 500XGLP, 600XGLP	YK300XHS, 400XHS	1000	75
–	YK500XC, 600XC	YK500XP, 600XP	YK500XS, 600XS	1500	88
YK550X, 500XG, 600XG	–	YK500XGP, 600XGP	YK500XGS, 600XGS	1700	93
–	YK700XC, 800XC, 1000XC	YK700XP, 800XP, 1000XP	YK700XS, 800XS, 1000XS	2000	100
YK600XGH, 700XG, 800XG, 900XG, 1000XG, 1200X	–	YK600XGHP, 700XGP, 800XGP, 900XGP, 1000XGP	YK700XGS, 800XGS, 900XGS, 1000XGS	2500	113

(2) When connected to 2 axis (Cartesian robot and/or multi-axis robot)

Axial current sensor value ^{Note}		Power capacity (VA)	Generated heat amount (W)
X axis	Y axis		
05	05	600	65
10	05	800	70
10	10	1000	75
20	05	1100	78
20	10	1300	83
20	20	1700	93

(3) When connected to 3 axis (Cartesian robot and/or multi-axis robot)

Axial current sensor value ^{Note}			Power capacity (VA)	Generated heat amount (W)
X axis	Y axis	Z axis		
05	05	05	700	68
10	05	05	900	73
10	10	05	1000	75
10	10	10	1200	80
20	05	05	1200	80
20	10	05	1300	83
20	10	10	1500	88
20	20	05	1600	90
20	20	10	1800	95
20	20	20	2000	95

(4) When connected to 4 axis (Cartesian robot and/or multi-axis robot)

Axial current sensor value ^{Note}				Power capacity (VA)	Generated heat amount (W)
X axis	Y axis	Z axis	R axis		
05	05	05	05	800	70
10	05	05	05	1000	75
10	10	05	05	1100	78
10	10	10	05	1300	83
10	10	10	10	1400	85
20	05	05	05	1200	80
20	10	05	05	1400	85
20	10	10	05	1500	88
20	10	10	10	1700	93
20	20	05	05	1600	90
20	20	10	05	1800	95
20	20	10	10	2000	100
20	20	20	05	2100	103
20	20	20	10	2200	105
20	20	20	20	2500	113

Note. Even if axial current sensor values for each axis are interchanged no problem will occur.

Note. Motor capacity vs. current sensor table

Connected motor capacity	Current sensor
100W or less	05
200W	10
400W or more	20

Note. Motor output of the B14H is 200W but the current sensor is 05.